



# PRODUCT DATASHEET

## Strada-D series

CITIZEN

<b>Ordering number</b>	<b>CA11243</b>		
<b>Description</b>	<b>CA11243-Strada-DW-tape</b>		
Family	Strada-D	FWHM	87+142 degrees
Type	Lens	Efficiency	92 %
LED	CL-L400	cd/lm	-
Color	Transparent	Gerber File	Available
Diameter	19.6 x 15.7 mm		
Height	10.15 mm		
Style	Rectangular		
Optic Material	PMMA		
Holder Material	-		
Fastening	Pin, tape		
Status	Ready		

<b>Ordering number</b>	<b>C11244</b>		
<b>Description</b>	<b>C11244-Strada-DN</b>		
Family	Strada-D	FWHM	104+60 degrees
Type	Lens	Efficiency	92 %
LED	CL-L400	cd/lm	-
Color	Transparent	Gerber File	Available
Diameter	19.6 x 15.7 mm		
Height	5.6 mm		
Style	Rectangular		
Optic Material	PMMA		
Holder Material	-		
Fastening	Glue, pin, screw		
Status	Ready		

<b>Ordering number</b>	<b>CA11245</b>		
<b>Description</b>	<b>CA11245-Strada-DN-tape</b>		
Family	Strada-D	FWHM	104+60 degrees
Type	Lens	Efficiency	92 %
LED	CL-L400	cd/lm	-
Color	Transparent	Gerber File	Available
Diameter	19.6 x 15.7 mm		
Height	5.75 mm		
Style	Rectangular		
Optic Material	PMMA		
Holder Material	-		
Fastening	Screw, tape, pin		
Status	Ready		

**NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.**



**GENERAL INFORMATION**

- Product series especially designed & optimized for CL-L400 series of LEDs.
- Special care taken to make light distribution as uniform as possible.
  
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: [http://www.ledil.com/datasheets/DataSheet\\_TAPE.pdf](http://www.ledil.com/datasheets/DataSheet_TAPE.pdf)
  
- Fastening to PCB with appropriate adhesive. By clicking link below you can find Ledil recommended glue options.  
[http://www.ledil.com/datasheets/DataSheet\\_GLUES.pdf](http://www.ledil.com/datasheets/DataSheet_GLUES.pdf)

**NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the tape.**

**NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.**

**If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.**

**Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.**

**NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the glue.**

**NOTE 2: All surfaces where glue is applied must be clean, dry and free from grease and dirt. If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer -this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.**

**Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.**