

## Visual Signals - Industrial LED ECO BEACONS

## Industrial LED ECO Beacons > **LEDD & LEDA 100 Series**

## Product overview


The LEDD & LEDA 100 economy series are suitable for light commercial & industrial signalling applications where local indication is required. These beacons have two selectable stages of alarm, flashing or continuous (static) mode, selectable by a jumper link on the PCB. The design also allows for a third wire connection giving flexibility to switch from a pre-set static mode to flashing.

The LED ECO range has been designed predominantly to offer a cost effective solution against more traditional

incandescent types of lamps, whether through new plant and machinery installations or existing facility upgrades. The design allows for termination inside the enclosure through the base of the beacon enclosure.

The LEDA version incorporates one piezo buzzer situated in the base of the unit that is synchronised to the flash rate (the buzzer cannot be controlled independently of the light) offering a combined audible & visual warning signal.





## LEDD & LEDA 100 Series > Ordering Information

Code No:	Voltage:	Light Source:	Current:
LEDD100-01	8-20v Ac/Dc	8 SMT LEDs	430mA •
LEDD100-02	20-30v Ac/Dc_~_	8 SMT LEDs	110mA ••
LEDD100-03	48v Ac ~	8 SMT LEDs	tba
LEDD100-05	40-380v Dc	8 SMT LEDs	35mA •••
	85-280v Ac ~		
LEDA100-01	8-20v Ac/Dc ~	8 SMT LEDs	430mA •
LEDA100-02	20-30v Ac ~	8 SMT LEDs	110mA ••
LEDA100-03	48v Ac ~	8 SMT LEDs	tba
LEDA100-05	40-380v Dc	8 SMT LEDs	35mA •••
	85-280v Ac ~		
• at 12v Dc	•• at 24v Dc	••• at 230v Ac	

ADD THE FOLLOWING LENS CODES TO THE PRODUCT WHEN ORDERING



02 04



UV Stable Polycarbonate Lens

Dustproof and Weatherproof

UV Stable ABS Plastic Base

· Continuously rated

· Low current consumption

· Optional wall bracket & guard available - see accessories

• 360° light output around the vertical axis

· Suitable for surface or wall mounting

· LED long life

• 3 point fix

**Kg** 0.14

50/60 **Hz** 



















