

Mains Socket Tester with RCD Test

multicomp PRO

**RoHS
Compliant**



Description

This mains socket tester can check socket-wiring errors. It is widely used in commercial and residential areas. It also include the leakage test feature to check whether circuit breakers are working properly.

Specifications	
Model	MP780683
Operating voltage	230V
Operating current	<18mA
Operating frequency	50Hz to 60Hz
RCD	~30mA
Indications	OK, leakage test passed
	OK
	Missing earth
	Missing live
	Missing neutral
	Live earth reverse
	Live earth reverse and missing earth

General Characteristics

Product colour	Green and Grey
Product net weight	80.5g
Product size	65mm × 65mm × 61mm

Part Number Table

Description	Part Number
Mains Socket Tester with RCD Test, EU Plug	MP780683

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

multicomp PRO